

## Resistor Color Code

Black	Brown	Red	Orange	Yellow	Green	Blue	Violet	Gray	White
0	1	2	3	4	5	6	7	8	9

### Tolerance Bands

Red	Gold	Silver	None
2%	5%	10%	20%

### How to read the code

- 1<sup>st</sup> Find the tolerance band normally not grouped with other 3 bands
- Starting from the other end, identify the first band – write down the number associated with that color
- Now read the next color and write down the number associated with it
- Then read the third color or the 'multiplier' band ( this number is the number of zeros)
- If the 'multiplier' band is gold move the decimal point one to the left. If the 'multiplier' band is silver move the decimal point two places to the left.

### Example 1:

Blue	Red	Red	Gold
1 <sup>st</sup> Significant Figure	2 <sup>nd</sup> Significant Figure	Multiplier	Tolerance
6	2	00	5%

6200 Ohm or 6.2K Ohm

### Example 2:

Brown	Black	Green	Red
1 <sup>st</sup> Significant Figure	2 <sup>nd</sup> Significant Figure	Multiplier	Tolerance
1	0	00000	2%

1000000 Ohm or 1Meg Ohm

### Example 3:

Gray	Orange	Violet	
1 <sup>st</sup> Significant Figure	2 <sup>nd</sup> Significant Figure	Multiplier	Tolerance
8	3	0000000	20%

830000000 Ohm or 830 Meg Ohm

For informational use only.

Although information is in compliance with industry standards, Abel Electronics cannot be responsible for any errors or misprints with the data above.